







## **Multifunction Generator 4x1**

**50 HZ** 

### **TECHNICAL SPECIFICATIONS**



### **MODEL**

# DG4X1

Gasoline generator 50 Hz with 3000 rpm Kholer Command Pro CH440 engine, 429 cc and 14 Hp. Engine stage V, with Epa emisions certificaton. 5 Kw, one phase. Mutlifunction genset: welder, generator, compressor and Led light tower

	GENERATOR		
Rated Output	5.000 w	Engine Displacement	429 cc
Maximum Output	5.500 w	Engine Power	14 Hp
Power Factor	1	<b>Emsion Certification</b>	STAGE V
Rated Voltage	230 V	Fuel Tank	30 L.
Frequency / Revolutions	50 Hz / 3000 rpm	Panel	Digital
Engine	KOHLER	Starting Method	Electric Key Start
Engine Model	Command Pro CH440	Battery	Included 12 AH

WELDER		COMPRESSOR	
Rated Duty Cycle	0,5	Fuel Tank Volume	20 L
Open Circuit Voltage	DC75V	Flow Capacity	100 L/min
Welding Current Range	50-200A	Pressure Rang	0,6 - 0,8 Mpa
Rated Current	180 A	Stage	1
Rated Voltage	27.2 V	LIGHTNING TOWER	
Welding Wires	Included (3 meters)	Lightning Lamp	LED / 4 x 100
Welding Rod	1,6 - 5 mm	Mast Height	4,5 m

**Features** 

Long Life Overhead Valve Engine Electric / Self Start for easy operate Low-Oil Shutdown To Prevent Engine Damage High Performance Alternator

Hardened Steel Tube Chassis Circuit Breaker Protected Outlets Low Tone Muffler

www.dalsongenerators.com